



# LOKI Warm-Air Hand Dryer

## 4000/4002/4004/4006



High-speed  
IR-sensor and electronic timer  
5-year warranty



DAN DRYER LOKI high-speed hand dryer; award winning and ADA compliant. Its elegant and functional design is characterised by clean lines and rectangular shapes, which complements the surrounding architecture. The robust front plate with the high light guide maintains the design theme throughout the LOKI range.

### Application

DAN DRYER LOKI is a compact, high-speed hand dryer in sleek design. Featuring short drying time and low maintenance, this reliable machine is suitable for all high traffic public and commercial areas.

### Technical data

Type	LOKI Prod. No.: 4000, 4002, 4004, 4006 Warm-air hand dryer with IR sensor
Dimensions	H 300 x W 173 X D 102 mm
Material	Brushed stainless steel
Drying cycle	10-15 sec.
Connection	230 V, 50/60 Hz, Class I 
Total wattage	1000 W
Noise level	69-76.6 dB @ 1 m
Max. air capacity	95-115 m/sec.
Net weight	5.0 kg
IP rating	IP24

### Tender text

Touch-free hand dryer in stainless steel, brushed or powder coated Infra-red sensor and electronic timer, drying cycle: 10-15 sec. IP24, 230 V, 50/60 Hz, 840-1000 W, Class I (earthed), 69-76.6 dB @ 1 m dBA.  
Net weight: 5.0 kg. H: 300mm, W: 173mm, D: 102mm.

### Approval

CE, WEEE, RoHS



### References

Offices and administration, shopping centres, restaurants, hotels, airports, schools and sports facilities.

### Standard colour

Prod. No. 4000: Brushed stainless steel  
Prod. No. 4002: RAL 9003, white, gloss 60  
Prod. No. 4004: RAL 9005, matt black, gloss 10  
Prod. No. 4006: RAL Classic colours

### Activation

Infrared sensor and electronic timer. Touch free. Activation distance adjustable 172 mm ( $\pm$  20 mm). Automatic stop after 60 seconds of continuous use.

### Motor type

Commutator motor with carbon brushes.  
16,000-29,000 revolutions/min.

### Protection

Automatic thermal cut-out in both motor and heating element.

### Installation

Machine intended for wall-mounting and fixed installation via circuit-breaker. Installation must be carried out by a qualified electrician.